

**DS-PR501-HWE**

Tri-X wireless receiver, compatible with AX Hybrid Pro control panel, used to expand wireless capability of the control panel. HIKVISION Tri-X detectors can be added to AX Hybrid Pro panel via this wireless receiver.

- 868MHz wireless receiver
- Wireless transmission distance up to 1600m
- Supports 32 wireless detectors, 8 wireless indoor sounders and 4 wireless outdoor sounders

## ▪ Specification

Software features		
Compatibility list	DS-PK1-E-WE	
	DS-PS1-I-WE	
	DS-PS1-E-WE	
	DS-PKF1-WE	
	DS-PDP15P-EG2-WE	
	DS-PDD12P-EG2-WE	
	DS-PDMCS-EG2-WE	
	DS-PDMC-EG2-WE	
	DS-PDWL-E-WE	
	DS-PDEB1-EG2-WE、 DS-PDEB2-EG2-WE	
	DS-PDEB1-EG2-WE(B)	
	DS-PDEB2-EG2-WE(B)	
	DS-PDP15P-EG2-WE(B)	
	DS-PDP18-HM-WE	
	DS-PDMC-EG2-WE(B)	
	DS-PDMCK-EG2-WE(B)	
	DS-PDBG8-EG2-WE	
	DS-PDTPH-E-WE	
	DS-PDCL12-EG2-WE	
	DS-PDC10DM-EG2-WE	
	DS-PDC10AM-EG2-WE	
	DS-PDTT15AM-LM-WE	
	DS-PDQP15AM-LM-WE	
	DS-PDSMK-E-WE	
	DS-PDHT-E-WE	
	DS-PDCO-E-WE	
Hardware features		
Bus	1 input for control panel connection and 1 output for bus extender	
Electrical characteristics		
Typical voltage	12 VDC	
Power supply	9-16VDC, up to 3A, provided by bus	
Power consumption	Quiescent Current	90 mA @12VDC
	Maximum Current	150 mA @12VDC
Wireless transmission		
RF frequency	868.0-868.6 MHz	
Wireless technology	Tri-X Wireless Technology	
RF distance 改为 : Transmission Range(Free Space)	1600m (Open area)	

## ▪ Available Model

DS-PR501-HWE

DS-PM643-WE(RU)



# See Far, Go Further



[www.hikvision.com](http://www.hikvision.com)  
[support@hikvision.com](mailto:support@hikvision.com)

